ELECTRONIC INNOVATIONS IN ACTION

SEMICONDUCTORS

Silicon Monolithic Darlington Amplifiers

PLANAR EPITAXIAL PASSIVATED

NPN

D16P1
D16P2
D16P3
D16P4

The General Electric D16P1, D16P2, D16P3 and D16P4 are planar epitaxial passivated NPN silicon Darlington monolithic amplifiers. They are ideal for preamplifier input stages requiring high input impedances of several megohms.



Features

- Low Cost • Very High Beta
- High Input Impedance





absolute maximum ratings: (25°C) (unless otherwise specified)

		D16P1 D16P2	D16P3 D16P4	
Voltages				
Collector to base	V_{CBO}	18	40	V
Collector to emitter	V_{CEO}	12	20	V
Collector to emitter	V_{CES}	18	40	V
Emitter to base	V_{EBO}	8	12	V
Current				
Collector (steady state)	I_C	200	200	mA
Base (steady state)	I_B	20	20	mA
Dissipation				
Total power (free air @ 25°C)	P_T	320	320	mW
Total power (free air @ 65°C)*	P_T	185	185	mW
Temperature				
Storage	T_S	−65 to +150		°C
Operating	T_j	−65 to +120		°C
Lead 1/16" ± 1/32" from case for 10 seconds maximum	T_L	260	260	°C

*Derate 3.4 mW/°C for increase in ambient temperature between 25 and 120°C.

electrical characteristics: (25°C) (unless otherwise specified)

STATIC CHARACTERISTICS

			Min.	Typ.	Max.	
Collector cutoff current						
(V_{CE} = 18V, V_{BE} = 0)	D16P1, 2	I_{CES}			100	nA
(V_{CE} = 18V, V_{BE} = 0, T_j = 100°C)	D16P1, 2	I_{CES}			20	μA
(V_{CE} = 40V, V_{BE} = 0)	D16P3, 4	I_{CES}			100	nA
(V_{CE} = 40V, V_{BE} = 0, T_j = 100°C)	D16P3, 4	I_{CES}			20	μA
Emitter cutoff current						
(V_{EB} = 8V)	D16P1, 2	I_{EBO}			100	nA
(V_{EB} = 12V)	D16P3, 4	I_{EBO}			100	nA

electrical characteristics (25°C): (unless otherwise specified) (cont'd)

			Min.	Typ.	Max.	
Collector emitter breakdown voltage						
(I_C = 10 mA, I_B = 0)	D16P1, 2	BV_{CEO}			12	V
	D16P3, 4	BV_{CEO}			20	V
Forward current transfer ratio						
(I_C = 2 mA, V_{CE} = 5V)	D16P1, 3	h_{FE}	2,000			
	D16P2, 4	h_{FE}	7,000		70,000	
(I_C = 100 mA, V_{CE} = 5V)	D16P1, 3	h_{FE}†	10,000			
	D16P2, 4	h_{FE}†	20,000			
Collector emitter saturation voltage						
(I_C = 200 mA, I_B = 0.2 mA)	D16P1, 2	$V_{CE(sat)}$†			1.4	V
	D16P3, 4	$V_{CE(sat)}$†			1.0	V
Base emitter saturation voltage						
(I_C = 200 mA, I_B = 0.2 mA)		$V_{BE(sat)}$†			1.5	V
Base emitter drive voltage						
(I_C = 200 mA, I_B = 0.2 mA)		V_{BE}†			1.5	V

DYNAMIC CHARACTERISTICS

Forward current transfer ratio						
(I_C = 2 mA, V_{CE} = 5V, f = 1 kHz)	D16P1, 3	h_{fe}	2,000			
	D16P2, 4	h_{fe}	7,000	15,000		
Input impedance						
(I_C = 2 mA, V_{CE} = 5V, f = 1 kHz)	D16P1, 2	h_{ie}			500	kΩ
	D16P3, 4	h_{ie}			650	kΩ
Forward current transfer ratio						
(I_C = 2 mA, V_{CE} = 5V, f = 20 MHz)		h_{fe}	3	8.4		
Output capacitance						
(V_{CB} = 10V, f = 1 MHz)		C_{cbo}		7.6	10	pF
Input capacitance						
(V_{EB} = 0.5V, f = 1 MHz)		C_{ebo}		10.5		pF

†Pulsed Measurement: Pulse width ≦ 300 μ sec., Duty cycle ≦ 2%



Printed in U.S.A.

SEMICONDUCTOR PRODUCTS DEPARTMENT
ELECTRONICS PARK SYRACUSE 1, N. Y.

GENERAL ELECTRIC

(In Canada, Canadian General Electric Company, Ltd., Toronto, Ont. Outside the U.S.A., and Canada, by: Electronic Component Sales, I.G.E. Export Division, 159 Madison Avenue, New York, N. Y. 10016)

ELECTRONIC INNOVATIONS IN ACTION

SEMICONDUCTORS

Semiconductor Application Information

200.01 4/67

Supersedes 200.01 2/67

NEW APPLICATION NOTES! SEE REVERSE SIDE

Semiconductor product application and circuit design information is provided in these application notes and article reprints from professional and technical journals. Prepared and written by General Electric's Semiconductor Application Engineering Center, these publications give you a valuable solid state reference library.

Particular publications which interest you may be ordered from: **General Electric Co., Distribution Services, Bldg. 6-208, 1 River Road, Schenectady, New York 12305**

PLEASE ORDER BY PUBLICATION NUMBER.

General References:

200.0 Abstracts of Application Notes, Articles and Manuals
450.52 Published product Specification Sheets
640.13 Product catalog with major specifications

1. General Applications for Signal Semiconductors

90.13 Some Large Signal Properties of Planar and Epitaxial Transistors
90.15 An Integrated Reference Amplifier for Precision Power Supplies
90.17 Understanding Snap Diodes
90.20 A Precision Current Supply using the Reference Amplifier
90.22 The 2N3605 in RTL Application
90.23 Economy Transistors in Linear Industrial Applications
90.36 Predicting Reverse Recovery Time of High Speed Semiconductor Junction Diodes
90.40 Controlled Conductance Application
90.47 The Logarithmic and Temperature Coefficient Characteristics of the 1N3605—1N3606 Diodes
90.50 An Economy Silicon Transistor with Wide Range Voltage & Current Capability—Characteristics & Applications for 2N3402-05 & 2N3414-17
90.56 Belting Out Plastic Transistors on Mechanized Assembly Lines
90.60 Application of Multi-pellet Diodes in DTL Circuits
90.61 DC Coupling of Multivibrators Using Multi-pellet Diodes
90.62 Y Parameters: Their Accuracy and Measurement
90.65 Optoelectronics—A new Dimension in Circuit Design

2. General Applications for Power Semiconductors

90.16 Silicon Controlled Switches
90.21 How to Suppress Rate Effect in PNPN Devices
90.57 Using the Silicon Bilateral/Unilateral Switch
90.58 Reversible Ring Counter Utilizing the Silicon Controlled Switch
200.1 Characteristics of Common Rectifier Circuits
200.5 General Electric Selenium Thyrector Diodes
200.8 Accommodating Inrush Currents With Silicon Controlled Rectifiers
200.9 Power Semiconductor Ratings Under Transient and Intermittent Loads
200.10 Overcurrent Protection of Semiconductor Rectifiers
200.11 Rectifier Voltage Transients: Their Generation, Detection and Reduction
200.15 Turn Off Time Characterization and Measurement of Silicon Controlled Rectifiers
200.19 Using Low Current SCR's
200.27 An Introduction to the Controlled Avalanche Silicon Rectifier
200.28 The Rating of SCR's When Switching Into High Currents
200.30 Capacitor Input Filter Design With Silicon Rectifier Diodes
200.32 A Variety of Mounting Techniques for Pres-Fit SCR's and Rectifiers
200.34 The Light Activated SCR
200.35 Triac Control for AC Power
200.36 The Solid State Thyratron
200.37 Increasing Power and Frequency with G-E's New Line of High-Speed SCR's and Power Diodes
200.38 Application of Fast Recovery Rectifiers
200.39 The Series Connection of Rectifier Diodes
200.42 Commutation Behaviour of Diffused High Current Rectifier Diodes
200.50 Mounting Press Pak Semiconductors
201.19 RF Filter Considerations for Triac and SCR Circuits
660.1 Silicon Controlled Rectifier—Interview With E. E. Von Zastrow
660.10 SCR's Break the Frequency Barrier
660.12 Better Utilization of SCR Capability with A-C Inductive Loads
660.13 The Rating and Application of SCR's Designed for Power Switching at High Frequencies
660.14 Basic Magnetic Functions in Converters and Inverters Including New Soft Commutation
671.1 Economy Power Semiconductor Applications
CP65-937 A Program Report on Solid State Appliance Controls
ETR-3960 G-E Electronic Components Hobby Manual ($1.50)*
ETR-3875A Silicon Controlled Rectifier Manual, 4th Ed., $3.00*

3. Transistor Circuits

90.3 Efficient High Quality Program Amplifier Circuits using the Industrial Silicon Series 2N2107, 2N2108 and 2N2196
90.5 Silicon Transistor Chopper for High Impedance Sources
90.6 Use of Complementary Transistors in Switching Circuits
90.7 Silicon Transistor Chopper for Low Impedance Sources
90.8 A High Performance Portable Broadcast Receiver using Silicon Planar Passivated Transistors
90.14 Tape Erase and Bias Oscillator
90.18 A Tuned R.F. Stage High Performance Portable Broadcast Receiver using Silicon Planar Passivated Transistors
90.24 A Ring Counter for Driving Incandescent Bulbs
90.25 Silicon Transistor Flashers
90.26 A Four Transistor Line Operated Radio Receiver
90.27 A Low Cost All Silicon F.M. Tuner
90.28 The Use of "y" Parameters in Transistor Circuit Design
90.30 Measurement of Stored Charge in High Speed Diodes
90.49 A High Performance Automobile Receiver with Economy Silicon Planar Epitaxial Transistors
90.51 Transistor Cascode in F.M. Tuner
90.52 An Economical Three-Stage Four-Transistor 10.7 MHz I.F. Strip
90.53 Practical Circuit Applications for the New D16U Dual Diode
90.54 Application of the D16U Dual Diode in a High Speed Bistable Multivibrator
90.59 Low Cost Audio for Line-Operated Radio, TV, Phonographs, Etc.
90.63 Simplified Transistor Color TV Processing Circuitry
450.37 Transistor Manual—7th Edition (Order by ETR 3296, $2.00)*

4. Silicon Controlled Rectifier Circuits

200.14 The Silicon Controlled Rectifier in Lamp Dimming and Heating Control Service
200.18 Fluorescent Lamp Dimming With SCR's and Associated Semiconductors
200.21 Three Phase SCR Firing Circuits for DC Power Supplies
200.31 Phase Control of SCR's With Transformer and Other Inductive AC Loads
200.33 Regulated Battery Chargers Using the Silicon Controlled Rectifier
200.40 Series Operation of SCR's
200.41 Simple Circuits for Triggering SCR's Into Fast-Rising Load Currents
200.43 Solid State Control for DC Motors Provides Variable Speed With Synchronous—Motor Performance
200.44 Speed Control for Shunt-Wound Motors
200.45 Temperature Controls Incorporating Zero Voltage Switching
200.46 AC Voltage or Current Regulator Featuring Closed-Loop Feedback Control
200.47 Speed Control for Universal Motors
200.48 Flashers, Ring Counters and Chasers
200.49 A Low-Cost, Ultrasonic-Frequency Inverter Using A Single SCR
201.1 A Plug-In Speed Control For Standard Portable Tools and Appliances
201.5 A High Frequency Inverter Circuit
201.6, 7, 9-11 Applications for C106 Economy SCR
201.12 500 Watt AC Line Voltage and Power Regulator
201.13 Universal Motor Control With Built-In Self-Timer
201.14 Automatic Liquid Level Control
201.15 Solid-State Control for Electric Blankets
201.16 Fan Motor Speed Control—"Hi-Intensity" Lamp Dimmer
201.17 Sequential Turn Signal System for Automobiles
201.18 High Voltage Power Supply for Low Current Applications
201.20 Proportional Zero Voltage Switching Temperature Control
201.21 On-Off Zero Voltage Switching Temperature Control
660.7 RFI-Less Switching with SCR's

5. Unijunction Applications

90.10 The Unijunction Transistor Characteristics and Applications
90.12 Unijunction Temperature Compensation
90.19 Unijunction Frequency Divider

6. Tunnel Diode Applications

90.32 Tunnel Diodes as Amplifiers and Switches
90.33 Tunnel Diode Sinewave Oscillators
90.37 Signal Considerations for Tunnel Diode use in Timepieces
90.42 Tunnel Diode—UHF-TV Tuner
90.43 A Tunnel Diode R.F. Radiation Detector
90.44 Practical Tunnel Diode Converter Circuit Considerations
90.45 Tunnel Diode Sinewave Oscillators
90.46 Tunnel Diode Remote Control Transmitter
90.66 Applications for the New Low Cost TD700 Series Tunnel Diodes

7. Test Circuits

201.3 Portable SCR and Silicon Rectifier Tester

*Order these Manuals from: General Electric Co., Dept. B, 3800 N. Milwaukee Ave., Chicago, Ill. 60641

PRINTED IN U.S.A.

SEMICONDUCTOR PRODUCTS DEPARTMENT
ELECTRONICS PARK SYRACUSE 1, N. Y.

GENERAL ELECTRIC

(In Canada, Canadian General Electric Company, Ltd., Toronto, Ont. Outside the U.S.A., and Canada, by: Electronic Component Sales, I.G.E. Export Division, 159 Madison Avenue, New York, N. Y. 10016)

Abstracts of New Application Information

A supplement to Semiconductor Applications, publication number 200.0

90.65 3/67

Optoelectronics - A New Dimension in Circuit Design

By O.A. Kolody 32 Pages

Theory of operation and the physics of light emitting devices and detectors is discussed. Device characteristics and circuit applications of optoelectronic devices such as injection lasers, visible and infrared light emitting diodes, photo diodes, phototransistors, light activated SCR's and SCS's are considered. Pertinent terminologies, design equations and procedures are included.

90.66 3/67

Application for the New Low Cost TD700 Series Tunnel Diodes

By W.R. Spofford 12 Pages

The introduction of the truly low cost planar tunnel diode (TD700 series) now makes this remarkable device available for general purpose applications. Device construction, theory and practical applications are presented.

200.19 1/67

Using Low-Current SCR's (Revision)

By D.R. Grafham 40 Pages

Theory and Application of General Electric Low Current SCR's - including the new plastic-encapsulated C106 types. Applications discussed include: flip-flops, temperature controls, time-delay circuits, motor-speed controls, power supplies, low-speed logic circuits, automotive ignition, proximity switches and many more.

200.33 12/66

Regulated Battery Chargers Using the Silicon Controlled Rectifier (Revision)

By D.R. Grafham 24 Pages

Chargers for lead-acid and vented nickel-cadmium batteries from 6 to 400 volts. Half-wave and full-wave fast-charging (high current) charger circuits use SCR's to automatically switch over to trickle charge when battery voltage reaches the fully-charged level. Appendix discusses transformer design.

200.49 2/67

A Low-Cost, Ultrasonic-Frequency Inverter Using a Single SCR

By N. Mapham 20 Pages

A single SCR inverter circuit is described which minimizes the cost of semiconductors and associated trigger circuitry. It is most useful in the power range of 250 watts to several kilowatts, and over the frequency range of 400 to 30,000 Hertz. This application note is directed to the power supply designer and uses BASIC computer language to prepare exact solutions to the circuit analysis leading to simple tabular design procedure.

200.50 3/67

Mounting Press Pak Semiconductors

By B.W. Jalbert 16 Pages

Novel construction of Press Pak permits new mounting techniques to be employed. Mounting considerations and device testing are discussed. Air-cooled and water-cooled applications are illustrated.

Particular publications which interest you may be ordered from: **General Electric Co., Distribution Services, Bldg. 6-208, 1 River Road, Schenectady, New York 12305**